


Dual NPN Small Signal Transistor



Features

- Epoxy meets UL-94 V-0 flammability rating
- Surface mount package ideally Suited for Automatic Insertion
- Reduces number of components and board space
- Part no. with suffix "Q" means AEC-Q101 qualified


Application

- Ideal for low power amplification and switching

Mechanical Data

- **Package:** SOT-363
- **Terminals:** Tin plated leads, solderable per J-STD-002 and JESD22-B102
- **Marking:** K1P

Equivalent circuit



■Maximum Ratings (Ta=25°C Unless otherwise specified)

Item	Symbol	Unit	Value
Collector-Base Voltage	V_{CBO}	V	75
Collector-Emitter Voltage	V_{CEO}	V	40
Emitter-Base Voltage	V_{EBO}	V	6
Collector Current -Continuous	I_C	mA	600
Total Device Dissipation (*)	P_D	mW	200
Thermal Resistance Junction to Ambient (*)	R_{thJA}	K/W	625
Junction Temperature	T_J	°C	150
Storage Temperature	T_{STG}	°C	-55 to +150

(*) Device mounted on FR-4 PCB 1.0 x 1.0 x 0.06 inch



MMDT2222AQ

■ Electrical Characteristics (Ta=25°C unless otherwise specified)

Item	Symbol	Unit	Conditions	Min	TYP	Max
Collector-base breakdown voltage	V_{CBO}	V	$I_C=10\mu A, I_E=0$	75		
Collector-emitter breakdown voltage	V_{CEO}	V	$I_C=10mA, I_B=0$	40		
Emitter-base breakdown voltage	V_{EBO}	V	$I_E=10\mu A, I_C=0$	6		
Collector cut-off current	I_{CBO}	nA	$V_{CB}=60V, I_E=0$			10
Collector cut-off current	I_{CEX}	nA	$V_{CE}=60V, V_{EB(off)}=3V$			10
Emitter cut-off current	I_{EBO}	nA	$V_{EB}=3V, I_C=0$			10
Base cut-off Current	I_{BL}	nA	$V_{CE}=60V, V_{EB(off)}=3V$			20
DC current gain	h_{FE1}		$V_{CE}=10V, I_C=0.1mA$	35		
	h_{FE2}		$V_{CE}=10V, I_C=1mA$	50		
	h_{FE3}		$V_{CE}=10V, I_C=10mA$	75		
	h_{FE4}		$V_{CE}=10V, I_C=150mA$	100		300
	h_{FE5}		$V_{CE}=1V, I_C=150mA$	35		
	h_{FE6}		$V_{CE}=10V, I_C=500mA$	40		
Collector-emitter saturation voltage	$V_{CE(sat)}$	V	$I_C=150mA, I_B=15mA$			0.3
Collector-emitter saturation voltage	$V_{CE(sat)}$	V	$I_C=500mA, I_B=50mA$			1
Base-emitter saturation voltage	$V_{BE(sat)}$	V	$I_C=150mA, I_B=15mA$			1.2
Base-emitter saturation voltage	$V_{BE(sat)}$	V	$I_C=500mA, I_B=50mA$			2
Transition frequency	f_T	MHz	$V_{CE}=20V, I_C=20mA, f=100MHz$	300		
Delay time	td	ns	$V_{CC}=30V, I_C=150mA, I_{B1}=15mA, V_{BE(off)}=-0.5V$			10
Rise time	tr	ns				25
Storage time	ts	ns	$V_{CC}=30V, I_C=150mA, I_{B1}=-I_{B2}=5mA$			225
Fall time	tf	ns				60

■ Ordering Information (Example)

PREFERRED P/N	PACKING CODE	UNIT WEIGHT(g)	MINIMUM PACKAGE(pcs)	INNER BOX QUANTITY(pcs)	OUTER CARTON QUANTITY(pcs)	DELIVERY MODE
MMDT2222AQ	F2	Approximate 0.009g	3000	30000	120000	7" reel



■ Characteristics (Typical)

Fig.1-Static Characteristic




Fig.2 - DC Current Gian




Fig.3 - Collect-Emittor Saturation Voltage




Fig.4 - Base-Emittor Voltage




Fig.5 - Base-Emittor On Voltage






Fig.6 - Cob/Cib— V_{CE}/V_{EB}






MMDT2222AQ

■SOT-363 Package Outline Dimensions



SYMBOL	DIMENSIONS			
	INCHES		Millimeter	
	MIN.	MAX.	MIN.	MAX.
A	0.035	0.043	0.900	1.100
A1	0.000	0.004	0.000	0.100
A2	0.035	0.039	0.900	1.000
b	0.006	0.014	0.150	0.350
c	0.004	0.010	0.100	0.250
D	0.071	0.087	1.800	2.200
E	0.045	0.053	1.150	1.350
E1	0.085	0.096	2.150	2.450
e	0.026TYP		0.650TYP	
e1	0.047	0.055	1.200	1.400
L	0.021REF		0.525REF	
L1	0.010	0.018	0.260	0.460
theta	0°	8°	0°	8°


■SOT-363 Soldering Footprint



Unit: mm



■ Marking Information



Note:

1. All marking is at middle of the product body
2. All marking is in laser marking
3. K1P is Marking Code
4. Body color: Black



MMDT2222AQ

Disclaimer

The information presented in this document is for reference only. Yangzhou Yangjie Electronic Technology Co., Ltd. reserves the right to make changes without notice for the specification of the products displayed herein to improve reliability, function or design or otherwise.

The product listed herein is designed to be used with automotive electronics, are not designed for use in medical, life-saving, lifesustaining, or military, Yangjie or anyone on its behalf, assumes no responsibility or liability for any damages resulting from such improper use of sale.

This publication supersedes & replaces all information previously supplied. For additional information, please visit our website [http:// www.21yangjie.com](http://www.21yangjie.com) , or consult your nearest Yangjie's sales office for further assistance.